

AMIRA SUP 5.4.13 メニュー

緑字 : SUP5.4新機能, 変更点

Menu

Recording

Recording Codec	ProRes 422LT/422/422HQ/4444/4444XQ/MPEG-2 HD422/ARRI RAW	*ARRI RAWはライセンスが必要
Resolution	S16HD/HD/2K/3.2K/4K UHD/2.8K	2.8KはARRI RAW設定時
Project settings		
Project rate	23.976p/24p/25p/29.97p/30p/48p/50p/59.94p/60p/50i/59.94i/60i	3.2K,4KUHDは23.976p~60p
Next reel count	001~999	
Camera index	A~Z	
Camera ID prefix	L/R	
Lens squeeze factor	1.0/1.3	1.3は3.2K,4KUHDのみ

Record mode

Record mode	Normal/Interval/Stop Motion	
Interval length	0h01m00s 0h00m01s~2h00m00s	撮影間隔
Burst length	0001frames 0001~2000frames	
Duration mode	Manual/Preset	実行時間の設定/マニュアル
Recording duration	00h00m00s~99h59m59s	収録にかかる時間
Resulting clip length	0h00m00s	収録したクリップの長さ
Stop motion beeper	<input type="checkbox"/>	

Rec beeper/tally

Rec start beeper	<input type="checkbox"/>	
Rec stop beeper	<input type="checkbox"/>	
Card full beeper	<input type="checkbox"/>	
Tally MVF-1	<input checked="" type="checkbox"/>	
Tally rear	<input checked="" type="checkbox"/>	

Prerecord max.duration 01~20s

Audio recording

Audio recording	<input type="checkbox"/>	
Channel 1 control	Manual/Manual(+L)/Auto	
Channel 1 gain	+00~30dB	
Channel 1 level		レベルメーター表示
Channel 2 control	Manual/Manual(+L)/Auto	
Channel 2 gain	+00~30dB	
Channel 2 level		レベルメーター表示

Media

Erase CARD A	→Erase CARD A? →ERASE	全データ消去 (約15秒)
Erase CARD B	→Erase CARD B? →ERASE	
Delete last clip CARD A	→DELETE →Confirm Delete	最後のクリップを消去
Delete last clip CARD B	→DELETE →Confirm Delete	
Prepare USB medium	→CONFIRM	USBメモリにフォルダ作成 (FAT32のみ)

Monitoring

EVF/Monitor		Monitorは、EVFのLCDモニタの事 (SDIではない)
Surround view	<input checked="" type="checkbox"/>	
Zoom position	Top left/Top center/Top right/Mid left/Eye level/Mid center/Mid right Bottom left/Bottom center/Bottom right	
Anamorphic desqueeze	<input type="checkbox"/>	3.2K,4KUHDのみ1.3x デスキューズ
Peaking		
Peaking mode	Color/Aperture	
Peaking level	5 1~20	
Peaking offset shift	+0 -5~5	
Color	Red/Green/Blue/Cyan/Magenta/Yellow/Black/White	

Settings		
EVF brightness	6	1~10
EVF gamma	Standard/Lifted	
EVF power	Auto/Off/On	
Monitor brightness	6	1~10
Monitor flip mode	Auto/Normal/Flipped	
EVF overlays		
Frame lines	<input checked="" type="checkbox"/>	
Center mark	Off/Dot/Small Dot/Cross/Small Cross	
Surround mask	Black Line/Colored Line/25,50,75%Mask	
Status info	Off/Overlay/Safe	Overlay : サラウンドビュー領域に表示される
Status components	OFFでもタリーとinfoマークは表示される	
Info 1	<input checked="" type="checkbox"/>	上下
Info 2	<input checked="" type="checkbox"/>	左右
Timecode	<input checked="" type="checkbox"/>	
Audio	<input checked="" type="checkbox"/>	
Lens data	<input type="checkbox"/>	
Lensfocus distance	<input checked="" type="checkbox"/>	
UDM	<input type="checkbox"/>	UDM(超音波測距計)の計測値表示
Monitor overlays		
Frame lines	<input checked="" type="checkbox"/>	
Center mark	Off/Dot/Small Dot/Cross/Small Cross	
Surround mask	Black Line/Colored Line/Semitransp. Mask	
Lens data	<input type="checkbox"/>	

SDI

SDI processing		
Surround view	<input checked="" type="checkbox"/>	
Exposure tool	<input type="checkbox"/>	
Peaking		
Peaking	<input type="checkbox"/>	
Peaking mode	Color/Aperture	
Peaking level	5	1~20
Peaking offset shift	+0	-5~5
Color	Red/Green/Blue/Cyan/Magenta/Yellow/Black/White	
Overlays		
Frame lines	<input checked="" type="checkbox"/>	
Center mark	Off/Dot/Small Dot/Cross/Small Cross	
Surround mask	Black Line/Colored Line/25,50,75%Mask	
Status info	Off/Overlay/Safe	Overlay : サラウンドビュー領域に表示される
Status components	OFFでもタリーとinfoマークは表示される	
Info 1	<input checked="" type="checkbox"/>	上下
Info 2	<input checked="" type="checkbox"/>	左右
Timecode	<input checked="" type="checkbox"/>	
Audio	<input checked="" type="checkbox"/>	
Lens data	<input type="checkbox"/>	
Lens focus distance	<input checked="" type="checkbox"/>	
UDM	<input type="checkbox"/>	UDM(超音波測距計)の計測値表示
Camera index letter	<input type="checkbox"/>	
Anamorphic desqueeze	<input type="checkbox"/>	3.2k,4KUHDのみ1.3x デスクイーズ

S16HD,HD,2K,ARRI RAWモード

SDI 1 format	422 1.5G/422 3G/444 3G	
SDI 1 frame rate		
	422 1.5G→ 23.976p/24p/25p/29.97p/30p/50i/59.94i/60i/23.976psf/24psf/25psf/29.97psf/30psf	
	422 3G → 48p/50p/59.94p/60p	
	444 3G → 23.976p/24p/25p/29.97p/30p	
SDI 1 3G level	Level A/B	
SDI 1 image	Clean/Processed	
SDI 2 : clone SDI 1	<input type="checkbox"/>	
SDI 2 format	422 1.5G/422 3G/444 3G	

SDI 2 frame rate	
422 1.5G	→ 23.976p/24p/25p/29.97p/30p/50i/59.94i/60i/23.976psf/24psf/25psf/29.97psf/30psf
422 3G	→ 48p/50p/59.94p/60p
444 3G	→ 23.976p/24p/25p/29.97p/30p
SDI 2 3G level	Level A/B
SDI 2 image	Clean/Processed SDI 1がCleanの時、変更可能
3.2K,4K UHDモード	
SDI 1 format	422 1.5G/422 3G/444 3G/DL 422 3G UHD/422 6G UHD/DL 422 6G UHD
SDI 1 frame rate	
422 1.5G	→ 23.976p/24p/25p/29.97p/30p/50i/59.94i/60i/23.976psf/24psf/25psf/29.97psf/30psf
422 3G	→ 48p/50p/59.94p/60p
444 3G	→ 23.976p/24p/25p/29.97p/30p
DL 422 3G UHD	→ 23.976p/24p/25p/29.97p/30p SDI 1/2を使用
422 6G UHD	→ 23.976p/24p/25p/29.97p/30p
DL 422 6G UHD	→ 48p/50p/59.94p/60p SDI 1/2を使用
SDI 1 3G level	Level A/B
SDI 1 image	Clean/Processed
SDI 2 : clone SDI 1	<input type="checkbox"/>
SDI 2 format	422 1.5G/422 3G/444 3G/422 6G UHD
SDI 2 frame rate	
422 1.5G	→ 23.976p/24p/25p/29.97p/30p/50i/59.94i/60i/23.976psf/24psf/25psf/29.97psf/30psf
422 3G	→ 48p/50p/59.94p/60p
444 3G	→ 23.976p/24p/25p/29.97p/30p
422 6G UHD	→ 23.976p/24p/25p/29.97p/30p
SDI 2 3G level	Level A/B
SDI 2 image	Clean/Processed SDI 1がCleanの時、変更可能
Frame lines	
Frame line	None/ARRI 1.33/1.78 Ana. 1.3x/1.78/1.85 Ana. 1.3x/1.85/2.39 Ana. 1 ADD/DELETE
Frame line color	Red/Green/Blue/Cyan/Magenta/Yellow/Black/White
Frame line intensity	1~4 4
User rectangles	Off/Rect1/Rect2/Rect1+2
User rectangle 1	Width/Height/Offset left/Offset top (000~999) / Reset All
User rectangle 2	Width/Height/Offset left/Offset top (000~999) / Reset All
Exposure tools	
Select EVF/Mon.exp.tool	Zebra/False Color
Select SDI exp.tool	Zebra/False Color
False color mode	Monitoring-based/Log C-based
Zebra setup	
Zebra mode	High/Mid/High+Mid
High zebra level	0~100%
High zebra color	Red/Green/Blue/Cyan/Magenta/Yellow/Black/White
Mid zebra level	0~100%
Mid zebra range	1~100%
Mid zebra color	Red/Green/Blue/Cyan/Magenta/Yellow/Black/White
EVF waveform	<input type="checkbox"/>
EVF waveform size	Small/Large
Monitor waveform	<input type="checkbox"/>
Monitor waveform size	Small/Large
Return in path config	
EVF/MONITOR	<input checked="" type="checkbox"/>
SDI 1	<input checked="" type="checkbox"/>
SDI 2	<input type="checkbox"/>
Color bars	<input type="checkbox"/>

System

Sensor	
Image sharpness set/active	0 -5~5
Image detail set/active	0 -5~5
Noise reduction	Off/Normal/Strong S16HD,3.2K,4K UHDモードのみ
Genlock sync	Off/SYNC IN/TC IN

Sync shift (+0.000us)	+384000~-384000(20000.000us~-20000.000us)	1=0.052us
Mirror image	Off/V/H/V+H	
Sensor temperature	Normal/High humidity	
User pixel masking		
User pixel mask active	<input type="checkbox"/>	
Install user pixel mask	No UPM	
Export user pixel mask		
Delete user pixel mask		
Grab raw image		
Fan mode	Regular/Rec low/Low Noise	
Power		
Bat onboard(BAT1)warning	13.5V 9.0~36.0V	
Bat onboard(BAT1)warning	10% 0~99%	
Bat in(BAT2)warning	22.0V 9.0~36.0V	
Bat unit preference	Volt/Percent	
Lens mount setting		
Focus unit	Lens default/Imperial/Metric	
Enable lens mount	<input checked="" type="checkbox"/>	
System time+date	Year/Month/Day/Hour/Minute /Timezone(info)/Daylight saving time(info) <input type="checkbox"/>	日本 : UTC +9h
Buttons+display		
Display style	Day/Night	Night : LCDグレーバック表示
Button brightness	0~3 1	
Lock config		
Camera buttons	Select all/none	<input type="checkbox"/>
+ switches	ND filter switch	<input checked="" type="checkbox"/>
	US switch	<input checked="" type="checkbox"/>
	EI switch	<input checked="" type="checkbox"/>
	WB switch	<input checked="" type="checkbox"/>
	AW button	<input checked="" type="checkbox"/>
	REC button	<input type="checkbox"/>
	User buttons 1-8	<input checked="" type="checkbox"/>
EVF buttons	Select all/none	<input type="checkbox"/>
	REC button	<input type="checkbox"/>
	PLAY button	<input checked="" type="checkbox"/>
	EXP button	<input checked="" type="checkbox"/>
	PEAK button	<input checked="" type="checkbox"/>
	VF1 button	<input checked="" type="checkbox"/>
	VF2 button	<input checked="" type="checkbox"/>
	[M] button	<input type="checkbox"/>
	Monitor buttons	<input checked="" type="checkbox"/>
	+ wheel	
Lens buttons	Select all/none	<input type="checkbox"/>
	RET button	<input type="checkbox"/>
	VTR button	<input type="checkbox"/>
Multicam		
Multicam	<input type="checkbox"/>	
SSCP device IP	192.168.001.001	
SSCP device port	07800	
Camera access protocol (CAP)		
CAP server enabled	<input type="checkbox"/>	
CAP server password	arri	パスワードを任意に入力
CAP client list		接続先の表示
Network/WiFi		
WiFi power	<input type="checkbox"/>	
WiFi mode	Host/Client	
WiFi host password	arriarri	Host設定時パスワードを任意に入力
WiFi network		Wifi接続先の表示
Wireless region setting	Europe/USA/Japan/SouthKorea/World	

LAN IP mode	DHCP/Static		
LAN static IP	192.168.000.100		
LAN static subnet	255.255.255.000		
Licensed features	DELETE/ADD/HW INFO/FEATURES	ライセンスをインストール	
Update	カメラアップデート		
COMPONENTS	Update MVF-1	MVF-1のみアップデート	
	Update lens mount	レンズマウントのみアップデート	
Language	English/中文		

Setup

User setups installed	DELETE/EXPORT/LOAD/SAVE/RENAME	カメラに設定のロード及びセーブ
User setups on USB	LOAD/SAVE/IMPORT	USBから設定のロード及びセーブ
Factory reset	工場出荷設定	

User buttons

Use r switch	None/Fps/Look/Shutter			
Button VF1	Off	以下から選択		
Button VF2	Off	EVF Status Info	SDI Zebra/FC	Color Bars
Camera user buttons	Button 1~8 Off	EVF Waveform	EI Increase	FrameGrab
WCU user buttons	Button 1~6 Off	EVF+Mon. Check Lc	EI Decrease	FrameLine Color
LBUS device user buttons	Button 1~1 Off	EVF+Mon. Desqueeze	FPS Increase	Iris Auto
GPIO user buttons	Off	EVF+Mon. Exp. Tool	FPS Decrease	Overlay Menu
GPIO box 0~9	Button 1~1 Off	EVF+Mon. Frame Line	ND Increase	Playback
Lens RET	Off	EVF+Mon. Peaking	ND Decrease	Prerecording
		EVF+Mon. Surround	Shutter Increase	Record Start/Stop
		EVF+Mon. Zebra/FC	Shutter Decrease	Return In
		EVF+Mon. Zoom	WB Increase	Select Card
		Monitor Waveform	WB Decrease	Stop Motion trigger
		Flip Monitor	Audio Solo	WiFi Power
		SDI Check Log C	Audio Ch1 Increase	
		SDI Desqueeze	Audio Ch1 Decrease	EFマウント装着時
		SDI Exp.Tool	Audio Ch1+2 Increase	EF Auto Iris
		SDI Frame Lines	Audio Ch1+2 Decrease	EF Open Iris
		SDI Peaking	Auto WB	EF Close Iris
		SDI Status Info	Bluetooth Talk-back	
		SDI Surround	Check Last Clip	

Metadata

Production	⇒	テキスト入力
Prod.Company	⇒	↓
Director	⇒	↓
Cinematographer	⇒	↓
Camera Operator	⇒	↓
Location	⇒	↓
Scene	⇒	↓
Take	⇒	↓
User info 1/2	⇒	↓